

# EMERGENCY BALLASTS

## T5, T8 & T12 Battery Packs



The fluorescent emergency ballast allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the ballast switches to the emergency mode and operates one or two of the existing lamps for a minimum of 90 minutes. The unit contains a battery, charger and inverter circuit in a single package. The ballast can be mounted in the wireway or on top of the fixture, and is UL listed for factory installation or retrofit applications, and also damp location listed.

ITEM NO.	LUMENS	WORKS WITH
BAL500	450-500	17W - 40W, 4 FT. Max, T8, T10, T12, Slimline
BAL650C-2	350-650	Quad or Triple 2-Pin Fluorescents
BAL650C-4	350-650	Quad or Triple 4-Pin Fluorescents
BAL700	700	17W - 215W, 8 FT. Max, T8, T10, T12, U-Lamp, Slimline
BAL1400	1100-1400	17W - 215W, 8 FT. Max, T8, T12, T12, U-Lamp, Slimline
BAL3000	3000	17W - 215W, 8 FT. Max, T8, T10, T12, BIAX, Slimline
BALT5-1300	1300	17W - 40W, T8, T10, T12, (1) 8W - 54W T5 & T5HO lamp



### Lamp Compatibility Chart

MODEL	BAL500	BAL650C-2	BAL700	BAL650C-4	BAL1400	BAL3000	BALT5
Lumens	500	600	700	650	1400	3000	1300
<i>Linear Lamps</i>							
2'-4' Rapid, Instant, or Energy Savings, T8-T12, HO, VHO	1		1 or 2	1	1 or 2	1 or 2	1
2'-8' Rapid, Instant, or Energy Savings, Circline T8-T12, HO, VHO			1		1	1	1
8W-28W - T5*	1		1		1 or 2	1 or 2	1
54W-T5HO					1 or 2	1 or 2	1
<i>Compact Fluorescent Lamps</i>							
13-39W Twin/Quad/TT - 4-pin (G24q/GX24q base)			1 or 2	1 or 2	1 or 2	1 or 2	
13-42W Twin/Quad/TT - 4-pin (G24q/GX24q base)			1	1	1	1 or 2	
10-26W Quad/TT - 2-pin (G24d/GX24d base)		1					
17W-40W 4-pin compact	1		1 or 2		1 or 2	1 or 2	1
40W-55W 4-pin compact			1		1	1	1
<i>Specialty Lamps</i>							
20-40W T9/T10/T12 Circline Lamps	1		1 or 2		1 or 2	1 or 2	
16-38W 2D - 4-pin (GR10q base)						1 or 2	
55W 2D - 4-pin (GR10q base)						1	1